



Image for illustration purposes only

# KMGP-169 GENSET

Generating Set Powered By Perkins STAMFORD LEROY-SOMER™

## Output Ratings

Speed, Frequency/Volt	Prime Power	Standby Power
1800rpm, 60 Hz/416-440V	122KWe / 153KVA	135KWe / 169KVA

## Genset Specifications

Engine Make & Model	Perkins 1106A-70TG1
Origin	UK
Alternator Type	UCI274E/TAL044H
Control Panel	Deep Sea - 6110 MKIII
Circuit Breaker Type	3 Pole MCCB
Tropical Cooling System	
Mechanical Governor	
Electrical Stop Solenoid, Energized to Run	
Compact Size	

Fuel System (prime)	50%	75%	100%
1800rpm, 60Hz (L/hr)	18.0	26.5	35.2

## International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



## RATING GUIDELINES

**PRIME POWER** rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

**MAXIMUM STANDBY POWER** rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

## Engine Technical Data

No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	105
Stroke, mm	135
Displacement, l	7.0
Compression Ratio	18.2:1
Starting	12V Electric
Alternators, Amps	12V/65A

## Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440/R120
Protection	IP23
Temperature Rise, °C	Prime 125/40
Regulation	±1.5%
No. of Phases	3
No. of Poles	4

## Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	2.55	0.9	1.45	1400	225
Enclosed	3.66	1.14	1.69	2150	195

For the enclosed type:-  
The sound level is around 85 dB(A) @ 3m.  
The height to be increased by 12cm for the hook.

# KMGP-169 GENSET

Generating Set Powered By  **Perkins** **STAMFORD LEROY-SOMER™**

Performances		1800rpm
<b>Alternator Efficiency</b>		91.4%
<b>Engine Power</b>		
Prime Power, KWm(hp)		133.5(179)
Standby Power, KWm(hp)		148.4(199)
<b>Alternator</b>		
Prime Power, KWe		128

Lubrication System		1800rpm
<b>Oil Consumption (l/hr)</b>		0.2% of fuel consumption
<b>Oil Sump Capacity, l</b>		14.9
<b>Oil System Capacity Include Filters, l</b>		18

Cooling System		1800rpm
<b>Heat Radiation from Engine and Alternator, Power KW</b>		27
<b>Heat Rejection to Coolant and Lube Oil at Standby Power, KW</b>		92
<b>Radiator Cooling Air Flow, m<sup>3</sup>/min (cfm)</b>		252(8899)
<b>Coolant Capacity, l</b>		21

Intake & Exhaust System		1800rpm
<b>Air Flow Combustion at Standby Power, m<sup>3</sup>/min(cfm)</b>		11.5(405)
<b>Heat Rejection Exhaust at Standby Power, KW</b>		-
<b>Exhaust Gas Temperature at Standby °C</b>		526
<b>Max Allowable Back Pressure in Exhaust Line, Kpa</b>		6.0
<b>Exhaust Gas Flow at Standby Power, m<sup>3</sup>/min(cfm)</b>		29.7(1050)

Accessories	
<b>Standard Silencer</b>	<b>Anti-Vibration Pads</b>
<b>Stainless Steel Flexible</b>	<b>Genuine Coolant 'Ready Mix'</b>
<b>Genuine Oil</b>	

Control Panel Readings
<ul style="list-style-type: none"> <li>• AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.</li> <li>• Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load</li> <li>• Oil pressure, water temperature, low oil level, high oil temperature</li> <li>• DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure</li> <li>• Low coolant level - Configurable inputs&amp;outputs</li> <li>• Upgradable for GSM network connection, Signal SMS messages.</li> </ul>

Optional Equipment
<ul style="list-style-type: none"> <li>• <b>Engine</b></li> <li>-Coolant heater</li> <li>-Oversize batteries</li> <li>-Extra fuel pre-filter water separator</li> <li>• <b>Alternator</b></li> <li>-Permanent magnet generator (PMG)</li> <li>-Upgrade to 3 phase sensing AVR</li> <li>-Qadrature droop kit</li> <li>-Anti-condensation heater</li> <li>-Air inlet filters</li> <li>• <b>General</b></li> <li>-Upgrade to modular controller for paralleling</li> <li>-Upgrade to 4 pole circuit breaker</li> <li>-Battery charger</li> <li>-Automatic transfer switch</li> <li>-Fuel level switch High / Low for alarm and control</li> <li>-Fuel transfer pump Automatic / Manual</li> <li>-Residential grade silencer</li> <li>-Weather protective and acoustic enclosure.</li> </ul>

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filter, full flow	(1)
Fuel filter	(2)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information
<b>Documentation</b> Engine instruction book-English Alternator manual- English Wiring diagram

**Warranty**  
 One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

