



# KMGC2250 GENSET

Generating Set Powered By



**STAMFORD** LEROY-SOMER™

## Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	1600KW <sub>e</sub> /2000kVA	1772KW <sub>e</sub> /2215kVA

## Genset Specifications

Engine Make & Model	Cummins QSK60-G4
Origin	UK
Alternator Type	S7L1D-G4I
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3Pole ACB
Water Cooling System	
Electronic Governor	
<b>Fuel System (prime)</b>	<b>50%</b> <b>75%</b> <b>100%</b>
1500rpm, 50 Hz (L/hr)	200      291      394

## International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



## RATING GUIDELINES

**PRIME POWER** rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

**MAXIMUM STANDBY POWER** rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

## Engine Technical Data

No. of Cylinders / Alignment	16/60° V
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	159
Stroke, mm	190
Displacement, l	60.2
Compression Ratio	16.2:1
Starting	24V Electric
Alternators, Amps	24V/55A

## Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX34I
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	±1%
No. of Phases	3
No. of Poles	4

## Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	6.1	2.54	3.15	15400	NA

# KMGC2250 GENSET

Generating Set Powered By



**STAMFORD LEROY-SOMER™**

© 2023 Khonaysser Group - All Rights Reserved

Performances 1500rpm	
<b>Alternator Efficiency</b>	96.0%
<b>Engine Power</b>	
Prime Power, KWm(hp)	1695(2273)
Standby Power, KWm(hp)	1861(2345)
<b>Alternator</b>	
Prime Power, KW	1664

Lubrication System 1500rpm	
<b>Oil Consumption (l/hr)</b>	-
<b>Oil Sump Capacity, l</b>	261
<b>Oil System Capacity Include Filters, l</b>	280

Cooling System 1500rpm	
<b>Heat Radiation from Engine and Alternator, Power KW</b>	175
<b>Heat Rejection to Coolant and Lube Oil at Standby Power, KW</b>	500
<b>Radiator Cooling Air Flow, m<sup>3</sup>/s</b>	34
<b>Coolant Capacity, l</b>	490

Intake & Exhaust System 1500rpm	
<b>Air Flow Combustion at Standby Power, m<sup>3</sup>/min(cfm)</b>	144.15(5090)
<b>Heat Rejection Exhaust at Standby Power, KW</b>	1325
<b>Exhaust Gas Temperature at Standby °C</b>	450
<b>Max Allowable Back Pressure in Exhaust Line, Kpa</b>	6.8
<b>Exhaust Gas Flow at Standby Power, m<sup>3</sup>/min(cfm)</b>	336.42(11880)

Accessories	
<b>Standard Silencer</b>	<b>Anti-Vibration Pads</b>
<b>Stainless Steel Flexible</b>	<b>Genuine Coolant 'Ready Mix'</b>
<b>Genuine Oil</b>	

## Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

## Optional Equipment

- **Engine**
  - Coolant heater
  - Oversize batteries
  - Extra fuel pre-filter water separator
  - Battery Disconnect Switch
  - Electrical Governor
- **Alternator**
  - Excitation Boost System (EBS)
  - Upgrade to 3 phase sensing AVR
  - Qadrature droop kit
  - Anti-condensation heater
  - Air inlet filters
- **General**
  - Upgrade to modular controller for paralleling
  - Upgrade to 4 pole circuit breaker
  - Battery charger
  - Automatic transfer switch
  - Fuel level switch High / Low for alarm and control
  - Fuel transfer pump Automatic / Manual
  - Residential grade silencer
  - Weather protective and acoustic enclosure.

## Spare Parts Kit (Optional) Genuine - Cummins

Oil filter	(4)
Fuel filter	(3)
Air filter	(4)
Fan belt set	(1)
Coolant filter	(2)

## General Information

**Documentation**  
 Engine instruction book-English  
 Alternator manual- English  
 Wiring diagram

**Warranty**  
 One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

