



KMGC-2500 GENSET

Generating Set Powered By



STAMFORD LEROY-SOMER™

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1800rpm, 60 Hz / 416V	1840KWe/2300KVA	2000KWe/2500KVA

Genset Specification

Engine Make & Model	Cummins QSK60-G6
Origin	UK
Alternator Type	S7LID-G4I
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3Pole ACB
Water Cooling System	
Electronic Governor	
Fuel System (prime)	50% 75% 100%
1800rpm, 60Hz (L/hr)	247 356 466

International Standards

Engine confirm to ISO 9001: 2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	16/60°V
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	159
Stroke, mm	190
Displacement, l	60.2
Compression Ratio	16.2:1
Starting	24V Electric
Alternators, Amps	24V/55A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX34I
Protection	IP23
Temperature Rise, °C	Prime 125 /40 Standby 163/27
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

KMGC-2500 GENSET

Generating Set Powered By



STAMFORD

LEROY-SOMER™

Performances	1800rpm
Alternator Efficiency	96%
Engine Power	
Prime Power, KWm(hp)	1937(2598)
Standby Power, KWm(hp)	2120(2843)
Alternator	
Prime Power, KWe	1880

Lubrication System	1800rpm
Oil Consumption (l/hr)	0.03
Oil Sump Capacity, l	261
Oil System Capacity Include Filters, l	280

Cooling System	1800rpm
Heat Radiation from Engine and Alternator, Power KW	210
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	620
Radiator Cooling Air Flow, m³/s	34
Coolant Capacity, l	490

Intake & Exhaust System	1800rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	174(6150)
Heat Rejection Exhaust at Standby Power, KW	1590
Exhaust Gas Temperature at Standby °C	475
Max Allowable Back Pressure in Exhaust Line, Kpa	6.8
Exhaust Gas Flow at Standby Power, m³/min(cfm)	439(15500)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
 - Battery Disconnect Switch
 - Electrical Governor
- **Alternator**
 - Excitation Boost System (EBS)
 - Upgrade to 3 phase sensing AVR
 - Qadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional) Genuine - Cummins

Oil filter	(4)
Fuel filter	(3)
Air filter	(4)
Fan belt set	(1)
Coolant filter	(2)

General Information

Documentation
 Engine instruction book-English
 Alternator manual- English
 Wiring diagram

Warranty
 One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

